TENTATIVE 2003.10.9

USB Driver Installation procedure (For Windows XP)

- Connect CP9000D/DW to PC with USB cable.
 Click Cancel, if "New Hardware Wizard" appears.
- (2) Open Device Manager.

Right click of My computer / Properties /Hardware /Device Manager.

Make sure that "USB printing support" is shown under a tree of Universal Serial Bus Controllers.



(3) Right click "USB printing support", then click " Update Driver..." to start "Hardware Update Wizard".

Select "Install from a list or specific location" and click "Next".



(4) Select "Don't search. I will choose the driver to install." and click "Next"

dware Update Wizard		
Please choos	e your search and installation options.	
O Search	for the best driver in these locations.	
Use the paths ar	check boxes below to limit or expand the default search, which includes local d removable media. The best driver found will be installed.	
🗹 S	earch removable <u>m</u> edia (floppy, CD-ROM)	
🗌 lr	clude this location in the search:	
	VENGLISHVWINXPVHOMEV	
Don't se Choose the drive	arch. I will choose the driver to install. This option to select the device driver from a list. Windows does not guarantee th r you choose will be the best match for your hardware.	
	<u>⟨B</u> ack <u>N</u> ext > Cancel	

(5) Click "Have Disk" and "Next".Select "inf" file from USBDRV / Win2000XP folder of supplied USB DLL files.

Select the device driver you want to install for this hardware.			
Select the manufacturer and model of your hardware device and then click Next. If you have a disk that contains the driver you want to install, click Have Disk.			
Show compatible hardware Model			
Support			
This driver is digitally signed. <u>Tell me why driver signing is important</u>	Have Disk		
	< <u>B</u> ack <u>N</u> ext > Cancel		



(6) Click "Finish".

(7) Make sure that in Device Manager,

"MITSHI USB Printer" port is created, instead of "USB printing port".



End of document.